



This section gives you all the information necessary to help you monitor and operate your controller including an Operator Interface overview, an explanation of the Displays, keys, LEDs, Mode access, and Operation Modes.




INPUT Sensor Range	J & K OR RTD & RTD.1 2W/3W (Configurable) (Also available in R/S/T/N/PT 1000) J(0°C to 400°C & 0°C to (600°C, K(0°C to 1200°C), PT-100 2W/3W(0°C to 400°C, - 50.0°C to 200.0°C)
OUTPUT Control Output Capacity SSR	RELAY + SSR 1CO, 7 Amp, 230 Volt AC 12 V DC Approximately
SPECIFICATIONS Supply Voltage Set Point Control Mode Operating Mode Accuracy Enclosure Material Operating Temperature Relative Humidity	230v AC, ±10%, 50Hz 1 Set Point Time Proportional / ON-OFF (Configurable) HEAT OR COOL Mode (Factory Set) ±1% of FSD Polycarbonate + ABS Plastic 0°C - 55°C Upto 95% RH Non Condensing
Note	Sensor Type R, S, T, E, B Available

CONNECTION DIAGRAM




MOUNTING

The controller can be mounted on either a vertical or tilted panel using the mounting bracket supplied. Adequate access space must be available at the back of the panel for installation and servicing activities. Overall dimensions and panel cutout requirements for mounting the controller are shown in Figure



Size	A	B	C	D	E	F	G	H(Min)	J	K(Min)
(96*96)	100	100	55	4	51	91	92	50	92	50
(96*48)	50	96	73	3	70	86	46	25	92	25
(72*72)	73.5	73.5	62	3	59	68	69	40	69	40
(48*48)	51	51	74	3	71	45	46	30	46	30
(48*96)	96	50	73	3	70	86	92	25	46	25

This section gives you all the information necessary to help you monitor and operate your controller including an Operator Interface overview, an explanation of the Displays, keys, LEDs, Mode access, and Operation Modes.



INPUT	Sensor Range	J & K OR RTD & RTD.1 2W/3W (Configurable) (Also available in R/S/T/N/PT 1000) J(0°C to 400°C & 0°C to (600°C, K(0°C to 1200°C), PT-100 2W/3W(0°C to 400°C, - 50.0°C to 200.0°C)
	Control Output Capacity SSR	RELAY + SSR 1CO, 7 Amp, 230 Volt AC 12 V DC Approximately
SPECIFICATIONS	Supply Voltage	230v AC, ±10%, 50Hz
	Set Point	1 Set Point
	Control Mode	Time Proportional / ON-OFF (Configurable)
	Operating Mode	HEAT OR COOL Mode (Factory Set)
	Accuracy	±1% of FSD
	Enclosure Material	Polycarbonate + ABS Plastic
	Operating Temperature	0°C - 55°C
	Relative Humidity	Upto 95% RH Non Condensing
Note		Sensor Type R, S, T, E, B Available

ORDER CODE	SIZE	DISPLAY	INPUT	OUTPUT	SUPPLY
DTC 9611-RO-JK-RS-S-N2-1	96 X 96	RED	J,K	RELAY + SSR	110 V - 240 V AC
DTC 9611-WO-JK-RS-S-N2-1	96 X 96	WHITE	J,K	RELAY + SSR	110 V - 240 V AC
DTC 9611-RO-RTD-RS-S-N2-1	96 X 96	RED	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 9611-WO-RTD-RS-S-N2-1	96 X 96	WHITE	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 7211-RO-JK-RS-S-N2-1	72 X 72	RED	J,K	RELAY + SSR	110 V - 240 V AC
DTC 7211-WO-JK-RS-S-N2-1	72 X 72	WHITE	J,K	RELAY + SSR	110 V - 240 V AC
DTC 7211-RO-RTD-RS-S-N2-1	72 X 72	RED	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 7211-WO-RTD-RS-S-N2-1	72 X 72	WHITE	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 4811-RO-JK-RS-S-N2-1	48 X 48	RED	J,K	RELAY + SSR	110 V - 240 V AC
DTC 4811-WO-JK-RS-S-N2-1	48 X 48	WHITE	J,K	RELAY + SSR	110 V - 240 V AC
DTC 4811-RO-RTD-RS-S-N2-1	48 X 48	RED	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 4811-WO-RTD-RS-S-N2-1	48 X 48	WHITE	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 4911-RO-JK-RS-S-N2-1	49 X 49	RED	J,K	RELAY + SSR	110 V - 240 V AC
DTC 4911-WO-JK-RS-S-N2-1	49 X 49	WHITE	J,K	RELAY + SSR	110 V - 240 V AC
DTC 4911-RO-RTD-RS-S-N2-1	49 X 49	RED	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 4911-WO-RTD-RS-S-N2-1	49 X 49	WHITE	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 9411-RO-JK-RS-S-N2-1	94 X 94	RED	J,K	RELAY + SSR	110 V - 240 V AC
DTC 9411-WO-JK-RS-S-N2-1	94 X 94	WHITE	J,K	RELAY + SSR	110 V - 240 V AC
DTC 9411-RO-RTD-RS-S-N2-1	94 X 94	RED	PT-100	RELAY + SSR	110 V - 240 V AC
DTC 9411-WO-RTD-RS-S-N2-1	94 X 94	WHITE	PT-100	RELAY + SSR	110 V - 240 V AC

Display Alphabet Characters

A	b	C	d	E	F	G	H	H	I	J	K	L	M	N	O	P	Q	R	S	T	U	V	W	X	Y	Z
A	B	C	D	E	F	G	H	H	I	J	K	L	M	N	O	P	Q	R	S	T	U	V	W	X	Y	Z

STARTING MENU

SET POINT SETTING

0035

Process Value

Press + /

0135

On Releasing Set Key Will Store the latest set value

0035

Process Value

POWER ON

0000

Display For 2 Sec

EC-J

Display For 2 Sec, According to the input sensor programmed

0-OF

Display For 2 Sec

0035

Process Value

DISPLAY MESSAGES

OFSE

Offset Value

EP

Time Proposal

I-PE

Input Type

EC-K

Input K Type

EC-J

Input J Type

SE

Set Value

C-L

Control Action

0-OF

Control Action

PB

Proportional band

CT

Cycle Time

HY

Hysteresis

MR

Manual Reset

PARAMETER SETTING

PASS

Press

0043

PASSWORD 30

0030

Press

OFSE

Offset Value
Use &

0000

Offset Value
Use &

L-rd

Low Range

0000

Set Low Range Value

H-rd

High Range

0600

Set High Range Value

- - - -

Save & Exit

PASSWORD 70

0070

Press

I-PE

Sensor Selection
Use &

EC-J

J/K Or Rtd/Rtd.1
Use &

C-L

Control Action
Use &

0-OF

TP/ON-OFF/PID
Use &

- - - -

Save & Exit

PASSWORD 90

0090

If TP

If ON-OFF

Press If PID

PB

Proportional band
Use &

0005

Use &

CT

Cycle Time
Use &

0004

Use &

MR

Manual Reset
Use &

0000

Use &

- - - -

Save & Exit

HY

Hysteresis
Use &

0002

Hysteresis
Use &

MODE

Mode Selection
Use &

HEAT

Heat/Cool
Use &

delta

Delay Time
Use &

0002

Use &

- - - -

Save & Exit

KP

Proportional Constant
Use &

0022

Use &

PI

Integral Constant
Use &

0222

Heat/Cool
Use &

KD

Derivation Constant
Use &

0055

Use &

CT

Cycle Time
Use &

0010

Use &

- - - -


Save & Exit

Measured Signal Specifications


Input type	symbol	Measuring range	Resolution	Accuracy	Input impedance/ auxiliary current
J		0~600°C	1°C	1.0%F.S±3digits	>500kΩ
K		0~1200°C	1°C	1.0%F.S±3digits	>500kΩ

ON-OFF Algorithm


When high accuracy of a temperature control is not required, Especially for the high time constant and small delay, it is possible to use ON-OFF control with hysteresis. Disadvantage of this method to use ON-OFF control with hysteresis. Disadvantage of this method is the occurrence of oscillations, even at small hysteresis values.

**TIME PROPORTIONAL ACTION:**


In this mode, ON & OFF time of output (Relay/SSR) varies proportionally in every cycle (cycle time settable by user) depending on the deviation of PV w.r.t. Set Value. This action Starts/continues only when PV enters or is within the band.

**MANUAL RESET (OFFSET ADJUSTMENT):**


In some application, after adopting Time proportionating action, system may stabilize at particular temperature over a period of time which can be different than the set value. This steady state (error) offset can be eliminated by setting this value equal and opposite to the existing offset.

**Load connection**

For Load Current Less Than 0.5A



For Bigger Loads, use Interposing relay / Contactor



Warranty and Application Considerations

Read and Understand This Catalog

Please read and understand this catalog before purchasing the products. Please consult your venex representative if you have any questions or comments.

Warranty and Limitations of Liability

WARRANTY

(12 Months, unless agreed otherwise by us) We undertake to replace or repair at our option any defective product that needs replacement or repair, by reason of defective workmanship or defective materials, brought to our notice within the period specified below as "Warranty Period" after delivery to the buyer, providing also that it we so require, the part in respect of which a complaint is made must, before liability can be entertained under this clause, be sent at buyer's expense to our works or our office, as we may determine. Under no circumstances do we undertake liability for indirect or consequential loss or damage of any nature. This guarantee is given in lieu of and excludes every other condition or warranty whether statutory or otherwise.

LIMITATIONS OF LIABILITY

VAPL Shall Not Be Responsible For Special, Indirect, Or Consequential Damages, Loss Of Profits, Or Commercial Loss In Any Way Connected With The Products, Whether Such Claim Is Based On Contract, Warranty, Negligence, Or Strict Liability.

In no event shall the responsibility of VAPL for any act exceed the individual price of the product on which liability is asserted

In No Event Shall VAPL Be Responsible For Warranty, Repair, Or Other Claims Regarding The Products Unless VAPL's Analysis Confirms That The Products Were Properly Handled, Stored, Installed, And Maintained And Not Subject To Contamination, Abuse, Misuse, Or Inappropriate Modification Or Repair.

Application Considerations

SUITABILITY FOR USE

VAPL shall not be responsible for conformity with any standards, codes, or regulations that apply to the combination of products in the customer's application or use of the products. Take all necessary steps to determine the suitability of the product for the systems, machines, and equipment with which it will be used.

Know and observe all prohibitions of use applicable to this product.

Never Use The Products For An Application Involving Serious Risk To Life Or Property Without Ensuring That The System As A Whole Has Been Designed To Address The Risks, And That The VAPL Products Are Properly Rated And Installed For The Intended Use Within The Overall Equipment Or System.

DISCLAIMERS

PERFORMANCE DATA

Performance data given in this catalog is provided as a guide for the user in determining suitability and does not constitute a warranty. It may represent the result of VAPL's test conditions, and the users must correlate it to actual application requirements. Actual performance is subject to the VAPL Warranty and Limitations of Liability.

CHANGE IN SPECIFICATIONS

Product specifications and accessories may be changed at any time based on improvements and other reasons. Consult with your VAPL representative at any time to confirm actual specifications of purchased product.

DIMENSIONS AND WEIGHTS

Dimensions and weights are nominal and are not to be used for manufacturing purposes, even when tolerances are shown.

SAFETY PRECAUTIONS

Do not touch the terminals while power is being supplied.
Doing so may occasionally result in minor injury due to electric shock.

Do not allow pieces of metal, wire clippings, or fine metallic shavings or filings from installation to enter the product. Doing so may occasionally result in electric shock, fire, or malfunction.

Do not use the product where subject to flammable or explosive gas.
Otherwise, minor injury from explosion may occasionally occur.

Never disassemble, modify, or repair the product or touch any of the internal parts. Minor electric shock, fire, or malfunction may occasionally occur

If the output relays are used past their life expectancy, contact fusing or burning may occasionally occur. Always consider the application conditions and use the output relays within their rated load and electrical life expectancy. The life expectancy of output relays varies considerably with the output load and switching conditions

Tighten the terminal screws to between 0.74 and 0.90 N.m. Loose screws may occasionally result in fire.

Set the parameters of the product so that they are suitable for the system being controlled. If they are not suitable, unexpected operation may occasionally result in property damage or accidents.

A malfunction in the Temperature Controller may occasionally make control operations impossible or prevent alarm outputs, resulting in property damage. To maintain safety in the event of malfunction of the Temperature Controller, take appropriate safety measures, such as installing a monitoring device on a separate line.



PRECAUTIONS FOR SAFE USE

Be sure to observe the following precautions to prevent operation failure, malfunction, or adverse effects on the performance and functions of the product. Not doing so may occasionally result in unexpected events.

- The product is designed for indoor use only. Do not use the product outdoors or in any of the following locations.
 - Places directly subject to heat radiated from heating equipment.
 - Places subject to splashing liquid or oil atmosphere.
 - Places subject to direct sunlight.
 - Places subject to dust or corrosive gas (in particular, sulfide gas and ammonia gas).
 - Places subject to intense temperature change.
 - Places subject to icing and condensation.
 - Places subject to vibration and large shocks.
- Use/store within the rated temperature and humidity ranges.
Provide forced-cooling if required.
- To allow heat to escape, do not block the area around the product.
Do not block the ventilation holes on the product.
- Be sure to wire properly with correct polarity of terminals.
- Use specified size (M3.5, width 7.2 mm or less) crimped terminals for wiring. To connect bare wires to the terminal block, use copper braided or solid wires with a rated temperature of over 70°C and a gauge of AWG24 to AWG14 (equal to a cross-sectional area of 0.205 to 2.081 mm²). (The stripping length is 5 to 6 mm.) Up to two wires of same size and type, or two crimped terminals can be inserted into a single terminal.
- Do not wire the terminals which are not used.
- Allow as much space as possible between the controller and devices that generate a powerful high-frequency or surge. Separate the high-voltage or large-current power lines from other lines, and avoid parallel or common wiring with the power lines when you are wiring to the terminals.
- Use this product within the rated load and power supply.
- Make sure that the rated voltage is attained within two seconds of turning ON the power using a switch or relay contact. If the voltage is applied gradually, the power may not be reset or output malfunctions may occur. into consideration when performing control.
- Make sure that the Controller has 30 minutes or more to warm up after turning ON the power before starting actual control operations to ensure the correct temperature display.
- A switch or circuit breaker should be provided close to this unit. The switch or circuit breaker should be within easy reach of the operator, and must be marked as a disconnecting means for this unit.
- Do not use paint thinner or similar chemical to clean with. Use standard grade alcohol.
- Design system (control panel, etc) considering the 2 seconds of delay that the controller's output to be set after power ON.
- The output may turn OFF when shifting to certain levels. Take this into consideration when performing control.
- The number of non-volatile memory write operations is limited

VBTRON AUTOMATION PVT. LTD.

132, Vishala industrial Estate,
Nr. Odhav Ring Road Circle,
Kathwada, Ahmedabad.
(GUJARAT) INDIA

Authorized Distributor :

© VBTRON AUTOMATION PVT. LTD. 2014
All Right Reserved. In the interest of
product improvement, specifications are
subject to change without notice.